



**Housing:** Stainless steel  
**Mounting:** Wall mounting  
**Protection category:** IP 65  
**Protection class:** III (Extra low voltage, supply via segment controller SEV)  
**Power consumption:** 2 arrows, dimmed approx. 0,9W  
 2x light output bottom side approx. .4,5W  
 2 arrows 100%≤3W pulsed  
 2 arrows permanent approx. 3W  
**Illuminant:** Green LED arrows  
 White LED for light output bottom side  
 Design life > 100 000 h  
**Functiontest:** Automatic via SEV and D.E.R. central.  
 Display of faulty luminaire at D.E.R. central.  
**Control:** Via D.E.R. central and segment controller (SEV) in relation/depending on the fire alarm panels status.  
 Luminaires can be set for synchronised run-light function.

Name:	<b>Becker</b>	Partnumber:	
Date:	<b>31.01.03</b>		
Change:		Description: <b>FS 7000 W</b> D.E.R.	Page: 1 von 1
Verified:			<b>INOTEC</b> Sicherheitstechnik GmbH